


# Oak 4-20 V1.3a

## 4-20mA Current Sensor including galvanic Isolation and 24V power supply

# Datasheet



Originally authored by Toradex AG. This work is now available under the terms and conditions of the Creative Commons License 'Attribution CC BY'

Details of which can be found here: <http://creativecommons.org/licenses/by/3.0/>



## Contents

1.	Introduction.....	3
1.1	Reference Documents .....	3
2.	Hardware Specifications.....	4
2.1	24V Power Supply .....	4
2.2	Current Measurement .....	4
2.3	Pin Assignment .....	4
2.4	Equivalent Output Circuit .....	4
2.5	Measurement Range.....	4
2.6	Supported Sensor Features .....	5
2.7	USB Interface .....	5
2.8	Operating Temperature Range .....	5
3.	Software Specifications .....	6
3.1	INTERRUPT IN Report Contents (Real time data) .....	6
3.2	FEATURE Report Commands.....	6
4.	Technical Specifications .....	9
4.1	Current Consumption .....	9
4.2	Mechanical Dimensions .....	9
4.3	RoHS Compliance .....	9
4.4	Pin Assignment USB Connector .....	10



## 1. Introduction

---

The Oak 4-20 is a USB attached precision current sensor. It is designed to be used with off-the-shelf sensors and instruments that offer a standard 4-20mA interface.

The external measuring interface is completely isolated from the USB circuit. In addition, Oak 4-20 provides a galvanically isolated 24V power supply, so the majority of external sensors can be attached without any additional hardware, using only two single wires.

To simplify installation, each Oak 4-20 has a disconnectable interface on the external side. The mating connector has screw terminals to allow a quick attachment of bare wires.

The Oak 4-20 can be integrated in a custom application very easily. The operating power as well as real time sensor data and uncritical sensor configuration data are all transferred through a simple USB cable. The very low power consumption, including automatic entering into sleep mode, allows using the device not only in fixed installations, but also in mobile applications.

### 1.1 Reference Documents

Programming Guide to the Oak Sensor Family



## 2. Hardware Specifications

### 2.1 24V Power Supply

The 24V power supply is galvanically isolated from the USB circuit. It supplies up to 30 mA on the external terminals.

The power supply has built-in short circuit protection.

### 2.2 Current Measurement

The current is measured using a 16 bit A to D converter, along with a high precision voltage reference.

### 2.3 Pin Assignment




Figure 1: Pin assignment

### 2.4 Equivalent Output Circuit




Figure 2: Equivalent output circuit

### 2.5 Measurement Range

Sensor data are provided in amperes:

Current	Range:	0 – 20.48 mA
	Resolution:	0.0012 mA



## 2.6 Supported Sensor Features

Read current in amperes

Sample rate adjustable

## 2.7 USB Interface

Interface: USB 2.0 Full Speed (12Mbits/s)

Connector: Standard USB Mini-B

Device Class: HID

Vendor ID: 0x1B67

Product ID: 0x0009

Sampling Rate: 148ms to 65s, user adjustable

Report Rate: 1 ms to 65s, user adjustable

## 2.8 Operating Temperature Range

Minimum Operating Temperature: -10°C

Maximum Operating Temperature: +85°C



### 3. Software Specifications

---

All Oak Sensors are implemented as HID devices. Thus driver support is built into all major operating systems.

Captured sensor Data is transmitted through an INTERRUPT IN reports. Therefore real time processing can be guaranteed. This data can be received by the host using regular file read operations. Chapter 3.1 describes the contents of this report.

On an independent communication channel, sensor configuration is done using FEATURE reports that are 32 Bytes in length. Special operating system calls exist to transmit / receive feature reports. Chapter 3.2 shows the structure of a feature report for each supported command.

Please refer also to the document “Programming Guide to the Oak Sensor Family” for more details.

#### 3.1 INTERRUPT IN Report Contents (Real time data)

16 Bit	Frame Number	$10^{-3}$	s
16 Bit	Current	$10^{-6}$	A

#### 3.2 FEATURE Report Commands

##### 3.2.1 Report Mode

Byte#	0	1	2	3	4	5
Content	GnS	Tgt	0x01	0x00	0x00	RPTMODE

GnS:           0 = Set  
               1 = Get

Tgt            0 = RAM  
               1 = Flash

RPTMODE:     0 = After Sampling (Factory Default)  
               1 = After Change  
               2 = Fixed Rate



## Oak 4-20 Datasheet

### 3.2.2 LED Mode

Byte#	0	1	2	3	4	5
Content	GnS	Tgt	0x01	0x01	0x00	LEDMODE

GnS:            0 = Set  
                  1 = Get

Tgt            0 = RAM  
                  1 = Flash

LEDMODE:    0 = Off (Factory Default)  
                  1 = On  
                  2 = Blink Slowly  
                  3 = Blink Fast  
                  4 = Blink 4 pulses

### 3.2.3 Report Rate

Number of milliseconds between two IN reports. This parameter will only be regarded if Report Mode = 2 (fixed rate)

Byte#	0	1	2	3	4	5	6
Content	GnS	Tgt	0x02	0x00	0x00	RptRate LSB	RptRate MSB

GnS:            0 = Set  
                  1 = Get

Tgt            0 = RAM  
                  1 = Flash

RptRate:       Report Rate [ms]

### 3.2.4 Sample Rate

This is the actual sample rate the sensor is working on. If Report Mode = 0 (After Sampling) this is also the rate at which the device reports values to the host PC.

Byte#	0	1	2	3	4	5	6
Content	GnS	Tgt	0x02	0x01	0x00	SampRate LSB	SampRate MSB

GnS:            0 = Set  
                  1 = Get

Tgt            0 = RAM  
                  1 = Flash

SampRate:      Sample Rate [ms]



## Oak 4-20 Datasheet

### 3.2.5 User Device Name

Byte#	0	1	2	3	4	5-25
Content	GnS	Tgt	0x15	0x00	0x00	UsrDevName

GnS:           0 = Set  
              1 = Get

Tgt           0 = RAM  
              1 = Flash

UsrDevName:   User defined name for the whole device  
              Null-terminated string, max. 20+1 characters

### 3.2.6 User Channel Name

Byte#	0	1	2	3	4	5-25
Content	GnS	Tgt	0x15	ChP1	0x00	UsrChName

GnS:           0 = Set  
              1 = Get

Tgt           0 = RAM  
              1 = Flash

ChP1          1 = Channel 0 (Frame Number)  
              2 = Channel 1 (Current)

UsrChName:    User defined name for the channel  
              Null-terminated string, max. 20+1 characters





## 4. Technical Specifications


### 4.1 Current Consumption

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
$I_q^{1)}$	Operating current				60	mA
$I_{Stby}$	Standby current	No USB activity			500	$\mu$ A

1) No external load current

### 4.2 Mechanical Dimensions

The PCB is designed to be mounted using two standard M2 screws. There are no components on the back side of the PCB, but there are through-hole components on top.





#### 4.4 Pin Assignment USB Connector

An additional crimped connector (X13) is provided for the USB interface. The connector is a 5 pin through-hole of the Picoblade family by Molex ([www.molex.com](http://www.molex.com)), reference 53047-0510.

Pin	Name	Function
1	Shield	Connected to GND on pcb
2	GND	Ground reference
3	D+	Positive USB data
4	D-	Negative USB data
5	USB_VCC	5V USB Supply from host



## Oak 4-20 Datasheet

### Revision history

Date	Changes
30-Apr-2012	Replace the drawings and add chapter about the Picoblade plug
29-Oct-2010	Added Operating Temperature Range
30-Sep-2010	Added USB Vendor ID and Product ID
24-Mar-2010	Corrected Measurement Range (section 2.5)
28-Feb-2008	Add Section Pin Assignment (section 2.3)
03-Sep-2007	Minor Edits (section 1.1)
21-May-2007	Preliminary Release

### Disclaimer:

Toradex AG reserves the right to make changes, without notice, to any product, including circuits and/or software described or contained in this datasheet.

Toradex AG assumes no responsibility or liability for the use of the described product(s), conveys no license or title under any patent, copyright, or mask work rights to these products, and makes no representations or warranties that these products are free from patent, copyright, or mask work right infringement, unless otherwise specified.

### Trademark Acknowledgement:

Brand and product names are trademarks or registered trademarks of their respective owners.